

**THE DISPLAY CHOICE
OF PROFESSIONALS™**

www.agneovo.com

CMS User Guide

TABLE OF CONTENTS

| | |
|---------------------------------|----|
| 1. Minimum Requirements..... | 2 |
| 2. Application | 3 |
| 3. Login..... | 7 |
| 4. Account | 7 |
| 5. Functions..... | 9 |
| 6. Content..... | 10 |
| 7. Schedule | 13 |
| 8. Publish..... | 15 |
| 9. Device..... | 17 |
| 10. Advanced | 19 |
| 11. Troubleshooting..... | 21 |
| 12. Content Design Support..... | 22 |



1. Minimum Requirements



| | |
|-----------------------|---------------------------|
| OS | Windows 7/8/10 |
| CPU | 2.5 GHz CPU or better |
| Memory (RAM) | 4 GB |
| Storage (HDD) | 100 GB |
| NIC / Ethernet | 10/100/1000 Ethernet Card |

2. Application

① Installation



Disable Firewall and
Antivirus first.





② Uninstall

This action will delete all data including the advanced-backup function data of CMS.



③ Version




④ Glossary

| Terms | Description |
|-----------------|-------------------------------------------------------------------|
| Group | Publish unit. You can group the devices. |
| Layout | You can design the content. |
| PIN Code | To setup the signage displays in OSD menu. |
| Template | You can choose one of the templates to design the layout content. |
| .bak | Backup file type. |
| .cms | Publish content file type. |
| .cmx | Layout file type. |


3. Login

Default account: admin

Default password: admin



4. Account




Account MGMT. — ①

Account Info — ②

Change Password — ③

Setting — ④

① Account MGMT. (Administrator Only)



- I. Create account: Please note, the default password of new created is “Ab123456”.

- II. Account lists: Your accounts are listed here.
- III. Activate account: Activate a selected account.
- IV. Delete account: Delete a selected account.
- V. Password reset: Admin can reset accounts password to the default “Ab123456”.

② Account info

You can change nickname here.


③ Change Password

You can change password here.


④ Setting

Enable wizard tips: You can enable wizard here. A wizard will give you hints for next step.

5. Functions




6. Content




① Create content

I. Create from templates :




II. Customized design :



The screenshot shows a dialog box titled "Please create the name of content" with a red close button in the top right corner. Below the title bar, there is a header "New Products" with a pencil icon. Three radio button options are listed: "Create from templates", "Customized design" (which is selected and circled in red), and "Import design". Below these options are two design aspect ratio icons: "Portrait (9:16)" represented by a blue rounded rectangle, and "Landscape (16:9)" represented by a yellow rounded rectangle with a pink inner border. A teal "NEXT" button with a refresh icon is located in the bottom right corner.

*Please refer to the “Content Design Support” page for creating customized content.

III. Import design :



The screenshot shows a dialog box titled "Please create the name of content" with a red close button in the top right corner. Below the title bar, there is a header "25% Off Campaign" with a pencil icon. Three radio button options are listed: "Create from templates", "Customized design", and "Import design" (which is selected and circled in red). Below these options is a teal "IMPORT FILE (.CMX)" button. A teal "NEXT" button with a refresh icon is located in the bottom right corner.

② Design orientation



③ Customized design

This icon denotes customized design.

④ Content lists

Your design will be listed here.

⑤ Next

Choose a content, and then edit it.

⑥ To schedule

Go to schedule management.

⑦ Rename content

Choose a content, and then rename it.

⑧ Copy content

Choose a content, and then have a copy.

⑨ Delete content


Choose a content, and then delete it.

⑩ Export content

Choose a content, and then export to a .cmx file.

7. Schedule

After selecting a group of displays, create or select a time slot, and then select contents and time to complete schedules.



① Create time slot

The minimal schedule unit is hour.

×

Please create the name of time slot

Time slot

Default

NEXT
↶

② Time slot lists

Your predefined time slots are listed here.

③ Next

Choose a time slot, and to edit it, then select contents and inputs specify playtime.

④ To publish

Go to publish management.

⑤ Rename time slot

Choose a time slot, and then rename it.


⑥ Delete time slot

Choose a time slot, and then delete it.

***Scheduling Limitations:**

1. Only daily scheduling is supported, scheduling does not support specific dates.
2. The time slot unit is one hour, minute or second-level scheduling is not supported.

8. Publish




① Group lists

A list shows groups that can receive content publish.

② Default layout


Click to change default layout.

System default :



③ Publish content

Click to publish and then you can download/copy a .cms file to a USB drive or any other place you like.



④ Publish history


The image shows a 'Publish History' table with a red close button in the top right corner. The table has four columns: 'Publish Time', 'Group', 'Time Slot', and 'Content'. There are two rows of data.

| Publish Time | Group | Time Slot | Content |
|------------------------|-------|---------------|--------------------------------------------------|
| 2015-10-06 16:37:39 | 1F | Opening hours | My image ads , My store ads , My promo ads |
| 2015-10-06 11:36:23 | 1F | Opening hours | My image ads |

⑤ To schedule

Click to go to schedule management.

9. Device



① Device setting

You need to setup the signage devices in OSD menu with account and pin code.

② Device lists

Binded devices will be shown here.

③ Device connected status

I. :  Online.

II. :  Offline.

II. : Offline.

④ Publish status

I. :  Devices update content successfully.

II. :  Devices download failure.

III. :  Devices run out of space.

IV. :  Content downloading.

⑤ Device detail

Show detail device info.

⑥ Group options

You can change group here.

⑦ Edit group name

You can change group name here.

⑧ Give device name

You can have a name for this device.

10. Advanced

① Instant broadcast



 Please select an instant broadcast type.

HURRICANE

FIRE

AMBER ALERTS

BLIZZARD

FLOODS

BOMB THREAT

TERROR ALERT

EARTHQUAKE

TORNADO

CUSTOM1

CUSTOM2

CUSTOM3

② Backup (Administrator Only)



Download the backup file? ✕

Backup procedure will take some time, please click the confirm button to continue.

✓ CONFIRM

③ Restore (Administrator Only)



Please select restore file ✕

RESTORE FILE(.BAK)

Restore procedure will take some time, please click the confirm button to continue.

✓ CONFIRM

11. Troubleshooting

| Appearance | Cause | Solution |
|-------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------|
| Content can't be published | The QM's Server IP (OPS Menu: Signage Display > CMS > Server) does not match the IP address for the software side. | Make sure the IP address for the software side matches the QM's Server IP. |
| Server and clients are in the same domain but client can't connect to server | May be problem of Windows Firewall and Antivirus software. | Disable the Windows Firewall and Antivirus software first to confirm. |

12. Content Design Support

① Text

| | |
|-------------------------------|-------------------------------------------------------------------------------------------|
| Static Text | One layout allows at most 50 static texts. |
| Marquee | One layout allows only one marquee. Marquee performance is very CPU/GPU intensive. |
| Breaking News/RSS Feed | One Layout allows at most 5 Breaking News and 5 RSS feeds at the same time. |

② Image

| | |
|------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| File & Size | JPEG and PNG files are supported. The maximum resolution is 3840x3160. The maximum image size is 15MB. For a better experience, images not exceeding 1920x1080 are recommended |
| Image | One layout allows at most 50 images |
| Slideshow | One layout allows at most 4 slideshows. For a better experience only one slideshow is recommended. Please note, the fluency of slideshows is very CPU/GPU dependent, results may vary according to your design. |

③ Video

| | |
|--------------------------|-------------------------------------------------------------------------------------------------------------------------------|
| format & size | Popular video formats MP4 and H.264 are supported. The maximum resolution is 1920x1080. The maximum filze size is 1GB. |
| Local Video | One layout allows only one video or one online video. |
| Online Video | Only YouTube online videos are supported. |

④ Widget

| | |
|----------------|---------------------------------------------------------------------------------------------------------------------------------|
| frame | One layout allows at most 50 frames. |
| webpage | One layout allows only one webpage widgets. Due to security reasons, some websites will prohibit the use of this widget. |
| Clock | One layout allows at most 2 clocks. |
| QR Code | One layout allows at most 2 QR Codes. |